

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48

Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67

Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70

Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04

Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93

Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29

Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес: rbt@nt-rt.ru | <http://rta.nt-rt.ru>

PLANETARY GEARBOXES SG SERIES



RTA presents in exclusive the new range of planetary gearboxes SG series that combine high performance with optimal reliability and represent a perfect PLUG AND GO solution with stepper and servo motors SANYO DENKI.

TECHNICAL SPECIFICATIONS:

- A wide range always available in stock at RTA
- Professional assembly and testing conducted in RTA to stepper and servo motors SANYO DENKI
- Excellent radial and axial load carrying capacity
- Low noise
- High precision
- High nominal and accelerants torque
- IP64 protection degree

PLANETARY GEARBOXES FOR STEPPING MOTORS



Model Name	Gearbox body (mm.)	Gear ratio	Maximum velocity (min-1)	Backlash (arcmin)	Emergency torque (Nm)	Motor coupling (Flange size)
SG-P11-050-003-12-HH-712X-00000	60	i=03	4000	12'	28	NEMA 23
SG-P11-050-003-12-HH-782X-00000	60	i=03	4000	12'	28	60 mm.
SG-P11-070-003-12-SM-286X-00000	85	i=03	4000	12'	60	NEMA 34
SG-P11-050-005-12-HH-712X-00000	60	i=05	5000	12'	30	NEMA 23
SG-P11-050-005-12-HH-782X-00000	60	i=05	5000	12'	30	60 mm.
SG-P11-050-005-12-SM-2861-00000	85	i=05	5000	12'	30	NEMA 34
SG-P11-070-005-12-SM-286X-00000	85	i=05	5000	12'	70	NEMA 34
SG-P11-050-009-12-HH-712X-00000	60	i=09	6000	12'	28	NEMA 23
SG-P11-070-010-12-HH-782X-00000	60	i=10	6000	12'	60	60 mm.
SG-P11-070-010-12-SM-2861-00000	85	i=10	6000	12'	60	NEMA 34
SG-P11-090-010-12-SM-286X-00000	85	i=10	6000	12'	150	NEMA 34

PLANETARY GEARBOXES FOR SERVO MOTORS



Model Name	Gearbox body (mm.)	Gear ratio	Maximum velocity (min-1)	Backlash (arcmin)	Emergency torque (Nm)	Motor coupling (Flange size)
SG-P11-070-005-12-R2-0X00-00000	60	i=05	5000	12'	70	60 mm.
SG-P11-090-005-12-R2-0750-00000	80	i=05	4500	12'	160	80 mm.
SG-P11-090-005-12-R2-1000-00000	90	i=05	4500	12'	160	100 mm.
SG-P11-070-010-12-R2-0X00-00000	60	i=10	6000	12'	60	60 mm.
SG-P11-090-010-12-R2-0400-00000	80	i=10	6000	12'	150	60 mm.
SG-P11-090-010-12-R2-0750-00000	80	i=10	6000	12'	150	80 mm.
SG-P11-120-010-12-R2-0750-00000	80	i=10	6000	12'	150	80 mm.
SG-P11-120-010-12-R2-1000-00000	100	i=10	5000	12'	300	100 mm.
SG-P11-090-025-15-R2-0X00-00000	80	i=25	4000	12'	160	60 mm.
SG-P11-120-025-15-R2-0750-00000	100	i=25	4500	12'	360	80 mm.
SG-P11-120-025-15-R2-1000-00000	100	i=25	4500	12'	360	100 mm.

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48

Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67

Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70

Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04

Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93

Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29

Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Единый адрес: rbt@nt-rt.ru | <http://rta.nt-rt.ru>